

ZyWALL 2 Plus Time Server Setup

步驟一：請先登入 ZyWALL 2 Plus 設備設定畫面 192.168.1.1，預設密碼為 1234。



步驟二：請於左邊功能列中點選 **MAINTENANCE**，並於 **Time and Date** 的頁面中點選 **Get from Time Server**，請選擇您所需的 **Time Protocol**(例：**NTP(RFC-1305)**)，並輸入欲同步化的 **Time Server Address**(例：**time.stdtime.gov**)，輸入完成後請點選 **Synchronize Now**，待完成後請點選 **Return** 回原設定畫面。



TIME AND DATE

System Time and Date Synchronization in Progress

The ZyWALL is attempting to synchronize with a time server! This may take up to one minute. Please wait...

TIME AND DATE

System Time and Date Synchronization Successful

Please click on Return to go to the Time and Date screen.

Return

步驟三：請於 **Time Zone** 選擇您所需要的時區與是否啟用日光節約(例：**(GMT+08:00)Taipei**)，完成後請點選 **Apply**。

MAINTENANCE

General	Password	Time and Date	Device Mode	F/W Upload	Backup & Restore	Restart
Current Time and Date						
Current Time		06:27:07 GMT				
Current Date		2007-09-27				
Time and Date Setup						
<input type="radio"/> Manual						
New Time (hh:mm:ss)		6 : 26 : 51				
New Date (yyyy-mm-dd)		2007 - 9 - 27				
<input checked="" type="radio"/> Get from Time Server						
Time Protocol		NTP (RFC-1305) ▼				
Time Server Address*		time.stdtime.gov			Synchronize Now	
* Optional. There is a pre-defined NTP time server list.						
Time Zone Setup						
Time Zone		(GMT+08:00) Beijing, Hong Kong, Perth, Singapore, Taipei ▼				
<input type="checkbox"/> Enable Daylight Saving						
Start Date		First ▼ Sunday ▼ of January ▼ (2007-01-07) at 0 o'clock				
End Date		First ▼ Sunday ▼ of January ▼ (2007-01-07) at 0 o'clock				
Apply Reset						

步驟四：設定完成後能於三處位置確認時間狀態。畫面中的 **Current Time&Date**。

MAINTENANCE

General	Password	Time and Date	Device Mode
Current Time and Date			
Current Time		14:29:06 GMT+08:00	
Current Date		2007-09-27	

Home 頁面下 System Information 中的 System Time。

System Information	
System Name	
Model	ZyWALL 2A
Bootbase Version	V1.08 12/29/2005
Firmware Version	V4.02(XU.0) 03/27/2007
Up Time	00:12:32
System Time	2007-09-27 14:30:29 GMT+08:00
Device Mode	Router
Firewall	Enabled

Logs 頁面下顯示各筆 Log 的發生時間。

LOGS

View Log Log Settings Reports

Logs

Display: All Logs Email Log Now Refresh Clear Log

#	Time ▲	Message	Source	Destination	Note
1	2007-09-27 14:30:58	firewall default policy: TCP (W to W/ZW)	59.115.153.229:2140	59.115.160.17:445	ACCESS DROPPED
2	2007-09-27 14:30:55	firewall default policy: TCP (W to W/ZW)	59.115.153.229:2140	59.115.160.17:445	ACCESS DROPPED
3	2007-09-27 14:30:44	ip spoofing - WAN UDP (W to W/ZW) (Repeated: 6)	169.254.71.249:137	169.254.255.255:137	ATTACK
4	2007-09-27 14:30:37	firewall default policy: TCP (W to W/ZW)	87.94.157.133:2632	59.115.160.17:445	ACCESS DROPPED
5	2007-09-27 14:30:31	firewall default policy: TCP (W to W/ZW)	87.94.157.133:2632	59.115.160.17:445	ACCESS DROPPED